



# 200A Mini Clamp Meters+Voltage Detector

Clamp meter with built-in AC Voltage detector + flashlight

**Features:**

- Measures 200A AC Current up to 100mA resolution
- 3% basic ACA accuracy
- 0.7" (18mm) jaw opening; 300MCM cable size
- 2000 count LCD display
- Non-contact AC Voltage detector (120/240VAC, 50/60Hz) via clamp tip
- Built-in white LED flashlight
- Measures Frequency up to 1kHz with 0.01Hz resolution
- Autoranging with Auto Power Off
- Data Hold
- Overload protection for all ranges
- Overrange and low battery indicators
- Complete with two AAA batteries

**MA120 additional features**

- 200A AC/DC Current
- Frequency measurement
- DCA zero key and backlit display



Bright LED Flashlight



Non-contact voltage detection via clamp tip

| Specifications             | MA100                      | MA120         |
|----------------------------|----------------------------|---------------|
| AC Current:                | 200A                       |               |
| DC Current:                | —                          | 200A          |
| Max Resolution:            | 0.1A                       |               |
| Basic ACA Accuracy (%rdg): | ±3%                        |               |
| AC Voltage (Max Res.):     | Non-contact                |               |
| Frequency (Max Res.):      | —                          | 1kHz (0.01Hz) |
| Dimensions:                | 6.5x2.6x1.3" (164x65x32mm) |               |
| Weight:                    | 6.2 oz (176g)              |               |

สนใจติดต่อ บริษัท เอมี่ท จำกัด 4/2,4/60,4/61 หมู่ 5 ถ.สุคนทรสวัสดิ์ แขวงลาดพร้าว เขตลาดพร้าว กทม. 10230

โทร.02-9079421-2 , 02-9077480-3, แฟกซ์ : 02-9079878 , Email : [sales@amet.net](mailto:sales@amet.net) , Web: [www.amet.net](http://www.amet.net)

