

## Megohm/Insulation Meter ( DIM 570)

### Model DIM 570

#### Features :

1. Measure insulation resistance up to 2000M $\Omega$
2. 1000V pulse to test insulation
3. 3 1/2 Digit LCD Back light display
4. Auto data hold function after releasing MEAS button
5. Auto power off function
6. Portability and simplicity for one hand operation
7. Valox housing to withstand accidental drops

#### Specifications:

- DIM 570 Specifications:
  - Measurement Range: 20M $\Omega$  [,2000M $\Omega$ ]
  - Accuracy:
    - 20M $\Omega$  [  $\pm$ 2.0%rdg + 2dgts),2000M $\Omega$  [ $<$ 500M $\Omega$  [  $\pm$ 4.0%rdg + 2dgts),  $\pm$ 5.0%rdg + 2dgts),
  - Test Voltage: 1000V DC approx.
  - Resolution: 10K $\Omega$ ]
  - Zero: Automatic
  - Polarity: Automatic positive implied, negative polarity indication
  - General
    - Power Requirement General
    - Power Requirement: 4 pieces 1.5V (AAA size) batteries
    - Dimensions: 6.7"x1.7"x1.6" (170x44x40mm)
    - Weight: 6.3 oz(180g)



Megohm/Insulation Meter  
DIM 570

Accessories: Test leads,Soft carrying case, batteries, owners manual.

