

## Pocket Foot Candle Light Meter



**Measures up to 2,000Fc**  
For basic lighting applications

### Features:

- Large 3 1/2 digit (1999 count) LCD with over-range indication
- Two ranges: 200.0 (0.1Fc) and 2000 (1Fc)
- 5% basic accuracy
- Precision color-corrected, photodiode sensor
- Battery operated with low battery indication
- Complete with 9V battery, remote light sensor with 45" (1.1m) cable, and built-in stand

### Applications:

- Workplace, cleanroom, and computer room light testing
- Compliance with safety regulatory bodies (OSHA)
- Ambient testing for light-sensitive archives such as in museums and art galleries
- Schools, library and parking lot light testing
- Building and ATM area security light monitoring



### Ordering Information:

401027.....Foot candle Light Meter

401027NIST .....401027 with Calibration Traceable to NIST .

สนใจติดต่อ บริษัท เอเม็ท จำกัด 31 ซอย โกสุมรวมใจ 37 แยก 2 แขวงดอนเมือง เขต ดอนเมือง กรุงเทพฯ. 10210

โทร.02-503-8900, แฟกซ์ : 02-981-0181, 02-981-0182 email : [sales@amet.net](mailto:sales@amet.net) , Web: [www.amet.net](http://www.amet.net)

