

## 400A AC/ DC Clamp-on Adaptor + NCV



### **AC/DC Current measurements to 400A**

*With built-in non-contact AC voltage detector*

#### **Features:**

- Fits virtually any MultiMeter with standard shrouded banana plug sockets
- Built-in non-contact voltage detector with LED alert
- 1.2" (30mm) clamp jaw
- Measures AC/DC Current in two ranges:  
0 to 40A (10mV per Amp output) and  
0 to 400A (1mV per Amp output)
- $\pm 2.5\%$  basic accuracy
- DC zero adjust
- Dims: 5.8 x 2.3 x 1.3" (146 x 60 x 32mm)  
Weight: 8oz (226g)
- Complete with built-in 3.8ft (1.1m) cable with banana plugs and two AAA batteries



Converts your MultiMeter into a 400A AC/DC Clamp Meter



#### **Ordering Information:**

**CA250** .....400A AC/DC Clamp-on Adaptor + NCV